AGRÓNIC 4500

FEATURES SUMMARY General motors or valves: 6 PUMPING Generator set or motor pump: 1 Pressure regulation Solar pumping, including summation of solar and grid power Filter groups with different times: 3 FILTERS Number of filters: unlimited Pressure reference for filter cleaning FROM 1 TO 4 HEADS Fertilizers: 8 FERTILIZATION Installation type: series, parallel or solar Each head has: Fertilization type: by CE, by CE input, Uniform, Proportional or Units (time or volume) pH regulation: 1 or 2 (can be base) Phytosanitary treatments: 2 Mix of two irrigation waters Tank volume control Number of sectors: 99 or 400 SECTOR For each sector: Volume and energy counter Flow detector Crop type and area for mass programming Pressure reference for irrigation Number of groups: 40 Number of sectors per group: 20 SECTOR GROUP Number of programs: 40 or 99 PROGRAMS IRRIGATION Number of subprograms or positions: 12 or 20 Number of sectors in each subprogram: 10 individual or 40 using groups Maximum number of sectors per program irrigating at the same time: 40 Number of conditional settings: 6 Start times: 6 Drainage control Number of drains for all programs: 20 Number of heads with solar irrigation: 1 SOLAR HYBRID Number of digital sensors: 80 DIGITAL ANALOG Number of analog sensors: 120 Number of meter sensors: 80 METERS Meters with pulse, analog and frequency output Measurement of volume, energy and units SENSORS Sum of several counters Number of logical sensors: 20 Number of inputs for each sensor: 5 I OGICAL Type of inputs: digital sensor, conditioning, digital output, logical sensor, sector, analog sensor, counter sensor and analog output. Addition, subtraction, average, AND and OR operations DETERMINING FACTORS Number of determining factors: 120 Number of foggers: 8 FOGGING Control by humidity / temperature or VPD Number of pivots: 4 **PIVOTS** Number of coordinators: 2 AGROBEE-L Number of modules for each coordinator: 20 Total number of modules: 40 EXTERNAL MODBUS Number of External ModBus devices: 32 Number of FAMs: 2 AGRÓNIC MONOCABLE EXTERNAL MODULES Number of MAM modules for each EAM: 120 Total number of modules: 240 Number of EARs: 2 AGRÓNIC RADIO Number of MAR modules for each EAM: 60 Total number of modules: 120 Number of Expansion Modules: 15 **EXPANSION MODULES** on Orange

BASIC version	Black	PIVOTS* functio
PLUS version	Blue	SOLAR* function

 SOLAR* function
 Red

 HYDRO function
 Green

* Functions available in the PLUS version